
**Information technology — Coding of
audio-visual objects —**

**Part 3:
Audio**

**AMENDMENT 6: Profiles, levels and
downmixing method for 22.2 channel
programs**

*Technologies de l'information — Codage des objets audiovisuels —
Partie 3: Codage audio
AMENDEMENT 6: .*



IECNORM.COM : Click to view the full PDF of ISO/IEC 14496-3:2009/AMD6:2017



COPYRIGHT PROTECTED DOCUMENT

© ISO/IEC 2017, Published in Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Ch. de Blandonnet 8 • CP 401
CH-1214 Vernier, Geneva, Switzerland
Tel. +41 22 749 01 11
Fax +41 22 749 09 47
copyright@iso.org
www.iso.org

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work. In the field of information technology, ISO and IEC have established a joint technical committee, ISO/IEC JTC 1.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular the different approval criteria needed for the different types of ISO documents should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see www.iso.org/directives).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation on the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT) see the following URL: www.iso.org/iso/foreword.html.

Amendment 6 to ISO/IEC 14496-3:2009 was prepared by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 29, *Coding of audio, picture, multimedia and hypermedia information*.

IECNORM.COM : Click to view the full PDF of ISO/IEC 14496-3:2009/AMD6:2017

Information technology — Coding of audio-visual objects —

Part 3: Audio

AMENDMENT 6: Profiles, levels and downmixing method for 22.2 channel programs

Page 31, 1.5.2.3

Replace:

Table 1.10 — Levels for the AAC Profile

Level	Max. channels/ object	Max. sampling rate [kHz]	Max. PCU	Max. RCU
1	2	24	3	5
2	2	48	6	5
3	NA	NA	NA	NA
4	5	48	19	15
5	5	96	38	15
6	7	48	25	19
7	7	96	50	19

with:

Table 1.10 — Levels for the AAC Profile

Level	Max. channels/ object	Max. sampling rate [kHz]	Max. PCU	Max. RCU
1	2	24	3	5
2	2	48	6	5
3	NA	NA	NA	NA
4	5	48	19	15
5	5	96	38	15
6	7	48	25	19
7	7	96	50	19
8	22	48	73	56
9	22	96	146	56

Page 36, 1.5.2.4

Insert the following new entries into Table 1.14 “audioProfileLevelIndication values” and adapt the “reserved for ISO use” range accordingly:

0x5D	AAC Profile	L8
0x5E	AAC Profile	L9
0x5F - 0x7F	reserved for ISO use	-

Page 13, 4.4.2.1

Replace:

Table AMD4.3 — Syntax of MPEG4_ancillary_data

Syntax	No. of Bits	Mnemonic
MPEG4_ancillary_data() {		
ancillary_data_sync;	8	bslbf
mpeg_audio_type	2	bslbf
dolby_surround_mode	2	bslbf
drc_presentation_mode	2	bslbf
stereo_downmix_mode;	1	bslbf
bs_info_reserved, set to “0”	1	bslbf
anc_data_status_reserved, set to “000”	3	bslbf
downmixing_levels_MPEG4_status	1	bslbf
ancillary_data_extension_status;	1	bslbf
audio_coding_and_compression_status	1	bslbf
coarse_grain_timecode_status	1	bslbf
fine_grain_timecode_status	1	bslbf
if (downmixing_levels_MPEG4_status == 1) {		
center_mix_level_on	1	bslbf
center_mix_level_value	3	bslbf
surround_mix_level_on	1	bslbf
surround_mix_level_value	3	bslbf
}		
If (audio_coding_mode_and_compression_status == 1) {		
audio_coding_mode_reserved	7	bslbf
compression_on	1	bslbf
compression_value	8	bslbf
}		
if(coarse_grain_timecode_status == 1)		
coarse_grain_timecode	16	bslbf
if(fine_grain_timecode_status == 1)		
fine_grain_timecode	16	bslbf
if (ancillary_data_extension_status == 1){		
reserved, set to “0”	1	bslbf
ext_downmixing_levels_status;	1	bslbf
ext_downmixing_global_gains_status;	1	bslbf
ext_downmixing_lfe_level_status;	1	bslbf
reserved, set to “0000”	4	bslbf
if (ext_downmixing_levels_status == 1){		
dmix_a_idx;	3	bslbf
dmix_b_idx;	3	bslbf
reserved, set to “00”	2	bslbf
}		

Table (continued)

Syntax	No. of Bits	Mnemonic
if (ext_downmixing_global_gains_status == 1) {		
dmx_gain_5_sign;	1	bslbf
dmx_gain_5_idx;	6	bslbf
reserved, set to "0"	1	bslbf
dmx_gain_2_sign;	1	bslbf
dmx_gain_2_idx;	6	bslbf
reserved, set to "0"	1	bslbf
}		
if (ext_downmixing_lfe_level_status == 1) {		
dmix_lfe_idx;	4	bslbf
reserved, set to "0000"	4	bslbf
}		
}		

with:

Table AMD4.3 — Syntax of MPEG4_ancillary_data

Syntax	No. of Bits	Mnemonic
MPEG4_ancillary_data() {		
ancillary_data_sync;	8	bslbf
mpeg_audio_type	2	bslbf
dolby_surround_mode	2	bslbf
drc_presentation_mode	2	bslbf
stereo_downmix_mode;	1	bslbf
bs_info_reserved, set to "0"	1	bslbf
anc_data_status_reserved, set to "000"	3	bslbf
downmixing_levels_MPEG4_status	1	bslbf
ancillary_data_extension_status;	1	bslbf
audio_coding_and_compression_status	1	bslbf
coarse_grain_timecode_status	1	bslbf
fine_grain_timecode_status	1	bslbf
}		
if (downmixing_levels_MPEG4_status == 1) {		
center_mix_level_on	1	bslbf
center_mix_level_value	3	bslbf
surround_mix_level_on	1	bslbf
surround_mix_level_value	3	bslbf
}		
If (audio_coding_mode_and_compression_status == 1) {		
audio_coding_mode_reserved	7	bslbf
compression_on	1	bslbf
compression_value	8	bslbf
}		
if (coarse_grain_timecode_status == 1)		
coarse_grain_timecode	16	bslbf
if (fine_grain_timecode_status == 1)		
fine_grain_timecode	16	bslbf
if (ancillary_data_extension_status == 1){		

Table (continued)

Syntax	No. of Bits	Mnemonic
reserved, set to "0"	1	bslbf
ext_downmixing_levels_status;	1	bslbf
ext_downmixing_global_gains_status;	1	bslbf
ext_downmixing_lfe_level_status;	1	bslbf
reserved, set to "0000"	4	bslbf
if (ext_downmixing_levels_status == 1){		
dmix_a_idx;	3	bslbf
dmix_b_idx;	3	bslbf
reserved, set to "00"	2	bslbf
}		
if (ext_downmixing_global_gains_status == 1) {		
dmx_gain_5_sign;	1	bslbf
dmx_gain_5_idx;	6	bslbf
reserved, set to "0"	1	bslbf
dmx_gain_2_sign;	1	bslbf
dmx_gain_2_idx;	6	bslbf
reserved, set to "0"	1	bslbf
}		
if (ext_downmixing_lfe_level_status == 1) {		
dmix_lfe_idx;	4	bslbf
reserved, set to "0000"	4	bslbf
}		
}		
ancillary_data_sync2;	8	bslbf
ext_downmixing_level_status2;	1	bslbf
if (ext_downmixing_levels_status2 == 1) {		
dmix_c_idx;	3	bslbf
dmix_d_idx;	3	bslbf
dmix_e_idx;	3	bslbf
dmix_f_idx;	3	bslbf
dmix_g_idx;	3	bslbf
dmix_l_idx;	4	bslbf
reserved, set to "0000"	4	bslbf
} else {		
reserved, set to "0000000"	7	bslbf
}		
byte_alignment();		
}		

Page 56, 4.5.2

In 4.5.2.14.1.1 “Data elements”, add the following elements:

ancillary_data_sync2	indicates the presence of MPEG-4 Audio ancillary data 2 and shall be set to 0xBD
ext_downmixing_levels_status2	indicates if downmixing coefficients for channelConfiguration = 13 exist
dmix_c_idx	indicates an index for the generation of a 5-channel downmix from 22-channel as shown in Tables AMD4.8 and AMD6.1
dmix_d_idx	indicates an index for the generation of a 5-channel downmix from 22-channel as shown in Tables AMD4.8 and AMD6.1
dmix_e_idx	indicates an index for the generation of a 5-channel downmix from 22-channel as shown in Tables AMD4.8 and AMD6.1
dmix_f_idx	indicates an index for the generation of a 5-channel downmix from 22-channel as shown in Tables AMD4.8 and AMD6.1
dmix_g_idx	indicates an index for the generation of a 5-channel downmix from 22-channel as shown in Tables AMD4.8 and AMD6.1
dmix_l_idx	indicates an index for LFE for the generation of a 5-channel downmix from 22-channel as shown in Tables AMD4.9 and AMD6.1

In 4.5.2.14.2 “Decoding process”, replace:

If a 2-channel stereo downmix is to be derived from a 6.1 or 7.1 stream,
with:

If a 2-channel stereo downmix is to be derived from a 6.1, 7.1 or 22.2 stream,

In 4.5.2.14.2.1 “Downmixing from 5.1 to Stereo/Mono”, replace:

Table AMD4.8 — Definition of mix level value

dmix_a_idx, dmix_b_idx surround_mix_level, “a” center_mix_level, “b”	Multiplication factor
000	1.0 (0dB)
001	0.841 (-1.5dB)
010	0.707 (-3dB)
011	0.596 (-4.5dB)
100	0.500 (-6dB)
101	0.422 (-7.5dB)
110	0.355 (-9dB)
111	0.000 (-∞dB)

with:

Table AMD4.8 — Definition of mix level value

dmix_a_idx dmix_b_idx dmix_c_idx dmix_d_idx dmix_e_idx dmix_f_idx dmix_g_idx surround_mix_level, “a” center_mix_level, “b”	Multiplication factor
000	1.0 (0dB)
001	0.841 (-1.5dB)
010	0.707 (-3dB)
011	0.596 (-4.5dB)
100	0.500 (-6dB)
101	0.422 (-7.5dB)
110	0.355 (-9dB)
111	0.000 (-∞dB)

In 4.5.2.14.2.1 “Downmixing from 5.1 to Stereo/Mono”, replace:

Table AMD4.9 — Definition of LFE mix level value

dmix_lfe_idx	Multiplication factor
0000	3.162 (+10dB)
0001	2.000 (+6dB)
0010	1.679 (+4.5dB)
0011	1.413 (+3 dB)
0100	1.189 (+1.5dB)
0101	1.0 (0dB)
0110	0.841 (-1.5dB)
0111	0.707 (-3dB)
1000	0.596 (-4.5dB)
1001	0.500 (-6dB)
1010	0.316 (-10 dB)
1011	0.178 (-15dB)
1100	0.100 (-20dB)
1101	0.032 (-30dB)
1110	0.010 (-40dB)
1111	0.000 (-∞dB)

with:

Table AMD4.9 — Definition of LFE mix level value

dmix_l_idx dmix_lfe_idx	Multiplication factor
0000	3.162 (+10dB)
0001	2.000 (+6dB)
0010	1.679 (+4.5dB)
0011	1.413 (+3 dB)
0100	1.189 (+1.5dB)
0101	1.0 (0dB)
0110	0.841 (-1.5dB)
0111	0.707 (-3dB)
1000	0.596 (-4.5dB)
1001	0.500 (-6dB)
1010	0.316 (-10 dB)
1011	0.178 (-15dB)
1100	0.100 (-20dB)
1101	0.032 (-30dB)
1110	0.010 (-40dB)
1111	0.000 (-∞dB)

After 4.5.2.14.2.2, insert the following subclause:

4.5.2.14.2.3 Downmixing from 22.2 to 5.1

Table AMD6.1 — Definition of downmixing_levels

Channel configuration	dmix_c_idx	dmix_d_idx	dmix_e_idx	dmix_f_idx	dmix_g_idx	dmix_l_idx
22.2 ch	g1	g2	g3	g4	g5	g6

$$C' = FC + g1 \times FLc + g1 \times FRc + g3 \times (TpFC + g4 \times TpC + BtFC)$$

$$L' = FL + g1 \times FLc + g2 \times SiL + g3 \times (TpFL + g2 \times TpSiL + BtFL)$$

$$R' = FR + g1 \times FRc + g2 \times SiR + g3 \times (TpFR + g2 \times TpSiR + BtFR)$$

$$Ls' = BL + g5 \times BC + g2 \times SiL + g3 \times (TpBL + g5 \times TpBC + g2 \times TpSiL + g4 \times TpC)$$

$$Rs' = BR + g5 \times BC + g2 \times SiR + g3 \times (TpBR + g5 \times TpBC + g2 \times TpSiR + g4 \times TpC)$$

$$LFE' = g6 \times (LFE1 + LFE2)$$

FLc and FRc mix level “g1”, side mix level “g2”, height mix level “g3”, TpC mix level “g4” and BC mix level “g5” are shown in Table AMD4.8. The LFE mix level “g6” shall be derived as shown in table AMD4.9.

FL, FR, FC, LFE1, BL, BR, FLc, FRc, BC, LFE2, SiL, SiR, TpFL, TpFR, TpFC, TpC, TpBL, TpBR, TpSiL, TpSiR, TpBC, BtFC, BtFL, and BtFR are the source signals and C', L', R', Ls', Rs', LFE' are the derived 5.1ch.

In 4.5.2.14.2.5 “Persistence of MPEG-4 ancillary data”, replace:

Table AMD4.12 — Default values after synchronization

Data field	Default value
dolby_surround_mode	“00”
drc_presentation_mode	“00”
center_mix_level_value	“010”
surround_mix_level_value	“010”
compression_on	“0”
compression_value	“0000 0000”
coarse_grain_timecode	“00 0000000000000000”
fine_grain_timecode	“00 0000000000000000”
dmix_a_idx	“010”
dmix_b_idx	“010”
dmx_gain_5	“000000”
dmix_gain_2	“000000”
dmix_lfe_idx	“1111”

with:

Table AMD4.12 — Default values after synchronization

Data field	Default value
dolby_surround_mode	“00”
drc_presentation_mode	“00”
center_mix_level_value	“010”
surround_mix_level_value	“010”
compression_on	“0”
compression_value	“0000 0000”
coarse_grain_timecode	“00 0000000000000000”
fine_grain_timecode	“00 0000000000000000”
dmix_a_idx	“010”
dmix_b_idx	“010”
dmix_c_idx	“011”
dmix_d_idx	“011”
dmix_e_idx	“000”
dmix_f_idx	“100”
dmix_g_idx	“010”
dmix_l_idx	“0111”
dmx_gain_5	“000000”
dmix_gain_2	“000000”
dmix_lfe_idx	“1111”

Extend Table 4.180 “Syntax of ELDSpecificConfig()” as follows:

4.6.20.3 ELDSpecificConfig

Table 4.180 — Syntax of ELDSpecificConfig()

Syntax	No. of bits	Mnemonic
ELDSpecificConfig (channelConfiguration)		
{		
frameLengthFlag;	1	bslbf
aacSectionDataResilienceFlag;	1	bslbf
aacScalefactorDataResilienceFlag;	1	bslbf
aacSpectralDataResilienceFlag;	1	bslbf
 ldSbrPresentFlag;	1	bslbf
If (ldSbrPresentFlag) {		
ldSbrSamplingRate;	1	bslbf
ldSbrCrcFlag;	1	bslbf
ld_sbr_header(channelConfiguration);		
}		
useLDQMFTTimeAligment = 0;		
while (eldExtType != ELDEXT_TERM) {	4	bslbf
eldExtLen;	4	uimbsf
len = eldExtLen;		
if (eldExtLen == 15) {		
eldExtLenAdd;	8	uimbsf
len += eldExtLenAdd;		
}		
if (eldExtLenAdd == 255) {		
eldExtLenAddAdd;	16	uimbsf
len += eldExtLenAddAdd;		
}		
switch (eldExtType) {		
case ELDEXT_SAOC:		
saocPresentFlag = 1;		
useLDQMFTTimeAligment = 1;		
SAOCSpecificConfig();		Note 1
break;		
case ELDEXT_LDSAC:		
ldmpsPresentFlag = 1;		
useLDQMFTTimeAligment = 1;		
LDSpatialSpecificConfig();		Note 1
break;		
case ELDEXT_DOWNSCALEINFO:		Note 2
downscaledSamplingFrequencyIndex	4	bslbf
if (downscaledSamplingFrequencyIndex == 0xf) {		uimbsf
downscaledSamplingFrequency	24	
}		
}		